FIBARO Home Center Lite

Model: FGHCL

Home Center Lite is an extremely compact controller using a web based and featuring graphic interface for simple programming. Control your house through a broad range of native apps, voice control by Google Assistant, Amazon Alexa or Apple Siri and Messenger. While creating Home Center Lite, we applied proven solutions used in our Home Center 2. Specially designed to your needs, Home Center Lite smoothly integrates with a broad range of multimedia systems and has a vast library of drivers for smart TV's, IP camera, and other 3rd party devices.







PRODUCT HIGHLIGHTS

- Extremely efficient, optimized hardware architecture,
- Ultra low energy consumption,
- Remote access via web page or mobile app,
- Simple, user-friendly interface,
- Fast and simple configuration,
- Manageable users' rights,
- Scenes and associations to benefit the most from your home system,
- Onditioning scenes depending on weather, state of devices or other, user-defined variables,
- Advanced recovery system,
- Oloud-based system backup,
- Measurable savings with comfortable heating panel,
- History of events.

© 2021 FIBAR GROUP S.A. fibaro.com

FIBARO Home Center Lite

TECHNICAL DATA

Processor	ARM Cortex-A8 (720MHz)
Case	Plastic
Operating memory	128 MB RAM
Hard drive	128 MB SLC HDD
Power supply	9-12 VDC (included)
Network interface	10/100/1000 Base-T (Gigabit) Ethernet via RJ45 connector
Operating temperature	10 – 40°C
EU standards compliance	RED 2014/53/EU, RoHS 2011/65/EU
Radio protocol	Z-Wave
Radio frequency	868.4, 868.42 or 869.8 MHz EU 908.4, 908.42 or 916.0 MHz US 921.4, 921.42 or 919.8 MHz ANZ 869.0 or 869.02 MHz RU
Range	up to 30m (98 ft (Depending on building structure)
Dimensions	90 x 90 x 33 mm

UNIT PACKAGE

Weight	0.54 kg
Length	12.8 cm
Width	12.8 cm
Height	11.2 cm
Pieces	1

COLLECTIVE PACKAGE

Weight	20 kg
Length	50 cm
Width	40 cm
Height	41 cm
Pieces	36

© 2021 FIBAR GROUP S.A. fibaro.com