

# FIBARO | The Button

## Model: FGPB-101 ZW5

FIBARO Button is a compact, battery-powered, Z-Wave Plus compatible device. It allows you to control devices through the Z-Wave network and run various scenes defined in FIBARO System. Different actions may be triggered with one to five clicks or by holding the button down. In panic mode, each press of the button results in triggering of the emergency scene. With its small design and wireless communication, the FIBARO Button can be conveniently mounted on any surface and in any position or location at home, e.g. beside the bed or under the desk.



## PRODUCT HIGHLIGHTS

- ✔ Compatible with Z-Wave and Z-Wave+ Controllers
- ✔ Supports protected mode (Z-Wave network security mode) with AES-128 encryption,
- ✔ Completely wireless with battery power and Z-Wave communication,
- ✔ May be installed anywhere in your home,
- ✔ Extremely easy installation - simply add and put on desired surface,
- ✔ Many colour variations: white, black, red, yellow, green, blue, brown and orange.

## COLOUR OPTIONS



FGPB-101-1



FGPB-101-2



FGPB-101-3



FGPB-101-4



FGPB-101-5



FGPB-101-6



FGPB-101-7



FGPB-101-8

### TECHNICAL DATA

Battery type	ER14250 ½AA, 3.6V DC battery (included)
Battery life	est. 2 years (with default settings)
Operational temperature	0 – 40°C
Radio protocol	Z-Wave (500 series chip)
Radio frequency	868.4, 869.85 MHz EU 908.4, 916.0 MHz US 921.4, 919.8 MHz ANZ 869.0 MHz RU
Compliance with	RoHS 2011/65/EU RED 2014/53/EU
Range	up to 40m (131 ft) (depending on building structure)
Dimensions (L x W x H)	46 x 34 mm

### UNIT PACKAGE

Weight	0.07 kg
Length	6.5 cm
Width	6.5 cm
Height	7.5 cm
Pieces	1

### COLLECTIVE PACKAGE

Weight	1.32 kg
Length	33.5 cm
Width	20.0 cm
Height	9.5 cm
Pieces	15